



Configuring the Verizon Motorola E815 for use with VRS Networks and the TSC2

The data plan required for Verizon is a “tethering plan”, designed to connect a laptop to a cell phone via a cable, using the cell phone as a modem.

Motorola V3m

1. With the phone turned on press center button on the 4-way navigation key.
2. Scroll to the right and select the Settings Icon. (screwdriver and wrench)
3. Scroll down and highlight Bluetooth.
4. Press the center button on the 4-way navigation key.
5. Look at the bottom left of the screen.
6. If you see On press the top left button to turn Bluetooth on.
7. If you see Off, Bluetooth is already turned on.

Creating a Bluetooth Connection with TSC2.

1. Turn on the TSC2 pressing and releasing the power button at the bottom left of the keyboard.
2. Tap on Start at the top left of the screen.
3. Tap on Settings.
4. Tap on the Connections Tab located at the bottom of the screen.
5. Tap on the Bluetooth icon.
6. Tap on the check box to Turn on Bluetooth.
7. Tap on the check box to Make this device discoverable to other devices.

Motorola V3m

1. Highlight Add New Device.
2. Press the center button on the 4-way navigation key.
3. You are asked to place device you are connecting to in discoverable mode.
4. Press the center button on the 4-way navigation key.

5. The Motorola V3m will start searching for your TSC2.
6. Highlight Your TSC2 with the serial number starting with SS.
7. Press the center button on the 4-way navigation key.
8. You are asked to enter a passkey.
9. Enter 0000 for the passkey.
10. Press the center button the 4-way navigation key.

Creating a Bluetooth Connection on the TSC2

1. The TSC2 asks the Motorola Phone wants to connect with your device Bluetooth. Do you want to add Motorola Phone to your device list.
2. Tap on Yes.
3. You are asked to enter a passkey.
4. Enter 0000 for the passkey.
5. Tap Next at the bottom right of the screen.
6. You should see the box checked for Dialup Networking.
7. Tap Finish at the bottom right of the screen.
8. Tap OK at the top right of the screen.

Motorola V3m

1. Under Add New Device you should see your TSC2 with its serial number.
2. Highlight your TSC2.
3. Press the top right button (Options).
4. Scroll down to highlight Incoming Security.
5. Press the center button the 4-way navigation key.
6. Highlight Automatic.
7. Press the center button the 4-way navigation key.

Creating a Network / Dial-up Connection on the TSC2

1. Tap on the Connections Icon.
2. Tap on Add a new modem connection under My ISP.
3. Enter V3m for the Name of the Connection.
4. Tap on the dropdown list for Select a Modem.
5. Select Bluetooth from the drop down list.
6. Tap Next.
7. Highlight Motorola Phone.
8. Tap Next.
9. Enter #777 for the phone number.
10. Tap Next.
11. User name – Your phone number@vzw3g.com. For example 1235551212@vzw3g.com. **Note: This is case sensitive.**
12. Password – vzw. **Note: This is case sensitive.**



13. Tap Finish.
14. Tap OK at the top right of the screen.
15. Tap X at the top right of the screen.

Testing Your Internet Connection between the Phone and the TSC2

1. Tap on Start.
2. Tap on Settings.
3. Tap on Connections.
4. Tap on Manage existing connections under My ISP.
5. Tap and hold on your connection.
6. Tap on Connect.
7. The “connecting” window will appear and dial the number.
8. When the window disappears, you are connected to the internet.
9. To disconnect tap on the icon to the left of the speaker icon at the top of the screen.
10. Tap on disconnect.